

## CATV/SAT Wall Socket


### NL8201 SAT Wall Sockets (5~2300MHz)

#### FEATURES

- Zinc die cast housing.
- All ports are F-(f) connectors, 75 ohm.
- Connectors:  
SAT:IEC 169-2(f).

■ Screening factor:

- 30-300MHz  $\geq 75$ dB
- 300-862MHz  $\geq 65$ dB
- 950-2400MHz  $\geq 55$ dB



NL8201

#### SPECIFICATIONS

Item	Frequency	NL8201
Insertion Loss IN-SAT	5~47MHz	$\leq 0.3$ dB
	47~860MHz	$\geq 0.5$ dB
	860~2150MHZ	$\leq 0.7$ dB
	2150~2300MHz	$\leq 1.0$ dB
Return Loss IN	5~47MHz	$\geq 12$ dB
	47~860MHz	$\geq 12$ dB
	860~2150MHZ	$\geq 10$ dB
	2150~2300MHz	$\geq 10$ dB
Return Loss SAT	5~47MHz	$\geq 20$ dB
	47~860MHz	$\geq 12$ dB
	860~2150MHZ	$\geq 10$ dB
	2150~2300MHz	$\geq 10$ dB